



# BAT54T /AT /CT /ST

#### SURFACE MOUNT SCHOTTKY BARRIER DIODE

#### **Features**

Ultra-Small Surface Mount Package

Low Forward Voltage Drop

Fast Switching

PN Junction Guard Ring for Transient and

**ESD Protection** 

Lead Free/RoHS Compliant (Note 3)

## **Mechanical Data**

Case: SOT-523

Case Material: Molded Plastic. UL Flammability

Classification Rating 94V-0

Moisture sensitivity: Level 1 per J-STD-020C

Terminals: Finish - Solderable per MIL-STD-202, Method 208


Lead Free Plating (Matte Tin Finish annealed over Alloy 42

leadframe).


Polarity: See Diagrams Below


Marking: See Diagrams Below & Page 2


Weight: 0.002 grams (approx.)
Ordering Information, see Page 2




SOT-523									
Dim	Min	Max	Тур						
Α	0.15	0.30	0.22						
В	0.75	0.85	0.80						
С	1.45	1.75	1.60						
D			0.50						
G	0.90	1.10	1.00						
Н	1.50	1.70	1.60						
J	0.00	0.10	0.05						
K	0.60	0.80	0.75						
L	0.10	0.30	0.22						
М	0.10	0.20	0.12						
N	0.45	0.65	0.50						
	0	8							
All Dimensions in mm									









#### Maximum Ratings @ T<sub>A</sub> = 25 C unless otherwise specified

Characteristic	Symbol	Value	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V <sub>RRM</sub> V <sub>R</sub> WM V <sub>R</sub>	30	V
Forward Continuous Current (Note 1)	I <sub>FM</sub>	200	mA
Repetitive Peak Forward Current	I <sub>FRM</sub>	300	mA
Forward Surge Current @ t < 1.0s	I <sub>FSM</sub>	600	mA
Power Dissipation (Note 1)	P <sub>d</sub>	150	mW
Thermal Resistance, Junction to Ambient (Note 1)	R JA	833	C/W
Operating and Storage Temperature Range	T <sub>j</sub> , T <sub>STG</sub>	-65 to +125	С


## Electrical Characteristics @ T<sub>A</sub> = 25 C unless otherwise specified


Characteristic		Min	Тур	Max	Unit	Test Condition
Reverse Breakdown Voltage (Note 2)		30			V	I <sub>R</sub> = 100 A
Forward Voltage	V <sub>F</sub>			240 320 400 500 1000	mV	I <sub>F</sub> = 0.1mA I <sub>F</sub> = 1mA I <sub>F</sub> = 10mA I <sub>F</sub> = 30mA I <sub>F</sub> = 100mA
Reverse Leakage Current (Note 2)	I <sub>R</sub>			2.0	Α	V <sub>R</sub> = 25V
Total Capacitance				10	pF	V <sub>R</sub> = 1.0V, f = 1.0MHz
Reverse Recovery Time	t <sub>rr</sub>			5.0	ns	$I_F = 10$ mA through $I_R = 10$ mA to $I_R = 1.0$ mA, $R_L = 100$


Notes: 1. Device mounted on FR-4 PC board with recommended pad layout, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf.


- 2. Short duration test pulse used to minimize self-heating efffect.
- 3. No purposefully added lead.











V<sub>R</sub>, INSTANTANEOUS REVERSE VOLTAGE (V) Fig. 3 Typical Reverse Characteristics

V<sub>R</sub>, REVERSE VOLTAGE (V) Fig. 4 Typical Capacitance vs. Reverse Voltage

## Ordering Information (Note 4)

Device	Packaging	Shipping		
BAT54T-7-F	SOT-523	3000/Tape & Reel		
BAT54AT-7-F	SOT-523	3000/Tape & Reel		
BAT54CT-7-F	SOT-523	3000/Tape & Reel		
BAT54ST-7-F	SOT-523	3000/Tape & Reel		

4. For Packaging Details: go to our website at http://www.diodes.com/datasheets/ap02007.pdf. Notes:

## **Marking Information**

XX = Product Type Marking Code (See Page 1, e.g. L1 = BAT54T) YM = Date Code Marking

Y = Year (ex: N = 2002) M = Month (ex: 9 = September)

Date Code Key

Year	20	02	2003	2004	2005	2006	2007	200	8 2	2009	2010	2011	2012
Code	٨	1	Р	R	S	Т	U	V		W	Х	Υ	Z
Month		Jan	Feb	March	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code		1	2	3	4	5	6	7	8	9	0	N	D



#### IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

#### LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.