

BB 121 A,B	Itt,Tho	C-Di	VHF/UHF Tuning, 30V, 0.6Ω(470MHz) A=2...2.35/11pF(25/3V), B=2.25...2.65/12pF(25/3V)	31a	DO-35	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 122	Itt,Tho	C-Di	VHF/UHF Tuning, 2.1...2.8/13pF(25/3V), 0.9Ω(300MHz)	31a	DO-35	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 125	ldr	C-Di	VHF/UHF Tuning, 30V, 2...3/12pF(25/3V)	31a	DO-35	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 126	ldr	C-Di	VHF/UHF Tuning, 30V, 2...3/11pF(25/3V)	31a	DO-35	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 130	Phi	C-Di	AM Tuning, 32V, 450...550/12...21pF(1/28V), <2Ω	7d	TO-92	BB 112, BB 509, MV 1401, 1SV134...135,++
BB 131	Phi	C-Di	SMD, TV VHF Tuner, 30V, 8...17/0.7...1pF(0.5/28V)	71a(1,7mm)	SOD-323	-
BB 132	Phi	C-Di	SMD, TV VHF Tuner, 30V, 60...75/2.3...2.75pF(0.5/28V)	71a(1,7mm)	SOD-323	-
BB 133	Phi	C-Di	SMD, TV VHF Tuner, ...460MHz, 30V, 42/2.4pF(0.8/28V)	71a(1,7mm)	SOD-323	-
BB 134	Phi	C-Di	SMD, TV UHF Tuner, 30V, 19/1.9pF(0.5/28V)	71a(1,7mm)	SOD-323	-
BB 135	Phi	C-Di	SMD, TV UHF Tuner, 30V, 19/1.9pF(0.5/28V)	71a(1,7mm)	SOD-323	-
BB 139	Fch,Itt,Tho	C-Di	VHF Tuning, FCCOIRT, 30V, 4.3...6/29pF(25/3V), 0.5Ω(300MHz)	31a	DO-35	BB 106, BB 209, BB 229, BB 309, BB 409
BB 141 A,B	Itt,Tho	C-Di	VHF/UHF Tuning, 30V, 0.6Ω(470MHz) A=2...2.35/11pF(25/3V), B=2.25...2.65/13pF(25/3V)	31a	DO-35	BB 121A,B, BB 205A,B, BB 405A,B, BB 505B
BB 142	Itt,Tho	C-Di	VHF/UHF Tuning, 30V, 2...3/12pF(25/3V), 0.9Ω(300MHz)	31a	DO-35	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 143 A,B	Itt	C-Di	FM/VHF Tuning, 30V, <0.7Ω(100MHz) A=5.3...5.9/9pF(25/10V), B=5.9...6.4/9pF(25/10V)	31a	DO-35	BB 109, MV 109, MV 2101...2115, 1SV50
BB 203	Sie	C-Di	=BB 103	31a	DO-35	=BB 103
BB 204	Phi,Sie,++	C-Di	=BB 104:	7e	TO-92	=BB 104
BB 205 A,B,G	Phi,Sie,++	C-Di	=BB 105 A,B,G	71a(4mm)	SOD-23	=BB 105A,B,G
BB 209(G)	Aeg,Phi,Sie	C-Di	VHF Tuning, 30V, 2,6...3/18...24pF(25/3V), 0,85Ω(330MHz) (BB 209G:	71a(4mm)	SOD-23 DO-7	BB 106, BB 229, BB 309, BB 409, ++
BB 212(B)	Phi	C-Di	Dual, AM Tuning, 12V, 500...620/22pF(0.5/8V), <2.5Ω	7e	TO-92	BB 107, BB 312
BB 215	Phi	C-Di	SMD, UHF Tuning, 30V, 1,8...2.2/17pF(28/1V), 0,63Ω	72a(3,4mm)	SOD-80	BB 621...623
BB 219	Phi	C-Di	SMD, VHF Tuning, 30V, 2,8...3.2/31(28/1V), <0.9Ω	72a(3,4mm)	SOD-80	BB 629, BB 631
BB 221	Itt,Tho	C-Di	=BB 121 A,B	31a	DO-35	=BB 121A,B
BB 222	Itt,Tho	C-Di	=BB 122	31a	DO-35	=BB 122
BB 229	Tho	C-Di	=BB 209:	31a	DO-35	=BB 209
BB 240	Phi	C-Di	SMD, VHF Tuning, Band B, ...400MHz 32V, 2,4...2.7pF/>0.5pF(28/0.5V), <1Ω(100MHz)	72a(3,4mm)	SOD-80	-
BB 241	Phi	C-Di	SMD, VHF Tuning, Band A, ...160MHz 32V, 2,5...3pF/>63pF(28/0.5V), <2Ω(100MHz)	72a(3,4mm)	SOD-80	-
BB 249	Phi	C-Di	SMD, VHF Tuning, FCC, OIRT 30V, 4...5pF/39...46pF(28/1V), <0.6Ω(200MHz)	72a(3,4mm)	SOD-80	-
BB 304	Aeg,Phi,Sie	C-Di	Dual, AM Tuning, 32V, 42...47.5pF(2V), 0,2Ω(100MHz)	7e	TO-92	BB 104, BB 204, MV 104, 1SV55, 1SV109
BB 305 B	Mot	C-Di	UHF Tuning, 35V, 2...2.3pF(25V), <0.8Ω	71a(4mm)	=SOD-23	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 305 G	Mot	C-Di	VHF Tuning, 35V, 1,8...2.8pF(25V), <1,2Ω	71a(4mm)	=SOD-23	BB 105G, BB 205G, BB 405G, BB 505G, ++
BB 309	Sie	C-Di	VHF Tuning, 30V, 3,7...4.5/56pF(28/1V), <0.7Ω(200MHz)	71a(4mm)	SOD-23	BB 106, BB 209, BB 229, BB 409, ++
BB 312	Sie	C-Di	Dual, AM Tuning, 32V, 485/26pF(1/30V), <2Ω(1MHz)	7e	TO-92	BB 107, BB 212
BB 313	Sie	C-Di	3-Di AM Tuning, 12V, 440...530/22pF(1/8.5V), <2.5Ω	5-SIP	-	BB 113, BB 413, MVAM-1
BB 314	Sie	C-Di	Dual, FM Tuning, 20V, 44.75/20.3pF(2/8pF)	7e	TO-92	BB 104, BB 204, BB 304, MV 104, 1SV 109
BB 319	Tho	C-Di	VHF Tuning	31a	DO-35	BB 106, BB 209, BB 229, BB 409, ++
BB 329 A,B	Itt	C-Di	VHF Tuning, 32V, 0,85Ω(330MHz) A=2.5...3.2/38pF(28/1V), B=2.8...3.2/38pF(82/1V)	31a	DO-35	BB 106, BB 209, BB 229, BB 409, ++
BB 404(A...E)	Aeg,Itt	C-Di	SMD, Dual, FM Tuning, 15V, 42...47.5pF(2V), 0,4Ω A=42...43.5, B=43...44.5, C=44...45.5pF(2V), D=45...46.5, E=46...47.5pF(2V)	35f	SOT-23	BB 804, BB 814
BB 405 A,B	Phi,Sie,Tho	C-Di	UHF Tuning, 30V, <0.8Ω(470MHz) A=2.2...2.5/15.5pF(25/1V), B=2...2.3/15.5pF(25/1V)	31a	DO-34	BB 205A,B, BB 505A,B, BB 505B, 1SV148,++
BB 405 G	Phi,Sie,Tho	C-Di	VHF Tuning, 30V, 1,8...2.5/15.5pF(25/1V), <1,2Ω	31a	DO-34	BB 205G, BB 505G, BB 609, 1SV124, ++
BB 406	Tho	C-Di	VHF Tuning, 28V, 4...5.1/25pF(25/3V), <0.6Ω(100MHz)	31a	DO-34	BB 106, BB 209, BB 229, BB 609, ++
BB 409	Sie	C-Di	VHF Tuning, FCC, OIRT, 30V, 4.5...5.6/26...32pF(25/3V)	31a	DO-35	BB 106, BB 209, BB 229, BB 609, ++
BB 413	Sie	C-Di	3-Di AM Tuning, 32V, 345...410/90...135pF(1/10V), <2Ω	5-SIP	-	BB 113, BB 313, MVAM-1
BB 417	Phi	C-Di	VHF/UHF AFC, 20V, 2,2...4/8...11pF(15/4V), <1,2Ω	31a	DO-34	BA 121, BB 117, 1SV89
BB 419	Sie	C-Di	SMD, VHF Tuning, 30V, 26...32/4,3...6pF(3/25V), <0.5Ω	71a(2,7mm)	SOD-123	-
BB 421	Tho	C-Di	UHF Tuning, 30V, 1,8...2.2(25V), <0.6Ω	31a	DO-34	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 422	Tho	C-Di	VHF Tuning, 30V, 1,8...2.6(25V), <0.9Ω	31a	DO-34	BB 205G, BB 405G, BB 505G, 1SV124, ++
BB 439	Sie	C-Di	=BB 419:	71a(1,7mm)	SOD-323	-
BB 501	Sie	C-Di	VHF/UHF AFC, 30V, 1,9...2.4/9...14pF(25/3V), 0,7Ω	7c	TO-92	BA 121, BB 117, BB 417, 1SV89
BB 502	Sie	C-Di	VHF AFC, 30V, 4,3...6/26...32pF(25/3V)	7c	TO-92	BB 119, 1SV114, 1SV125, 1SV145...146
BB 503	Sie,Tho	C-Di	=BB 501: SMD	35p	SOT-23	-
BB 503 DK	Tho	C-Di	=BB 501: SMD, Dual	35f	SOT-23	-
BB 504	Sie,Tho	C-Di	=BB 502: SMD	35p	SOT-23	-
BB 505 B	Aeg,Sie	C-Di	UHF Tuning, 30V, 2...2.3/17pF(25/1V), <0.8Ω(470MHz)	31a	DO-35	BB 205A,B, BB 405A,B, 1SV110...113,++
BB 505 G	Aeg,Sie	C-Di	VHF Tuning, 30V, 1,8...2.5/17pF(25/1V), <1,2Ω(470MHz)	31a	DO-35	BB 205G, BB 405G, 1SV97, 1SV124,++
BB 509	Itt	C-Di	AM Tuning, 4.43MHz-AFC, 440...600/20...40pF(1/8.5V)	7c	TO-92	-
BB 510	Itt	C-Di	SMD, Dual, AM Tuning, 12V, 440...600/20...40pF(1/9V)	35g	SOT-23	-
BB 512	Sie	C-Di	SMD, AM Tuning, 12V, 440...520/17...34pF(1/8V), 1,4Ω	71a(2,7mm)	SOD-123	-
BB 515 B,G	Phi,Sie	C-Di	SMD, VHF/UHF Tuning, 1,85...2.25/16...19.5pF(28/1V) B=1,85...2,25/17.7pF(28/1V), G=1,8...2,4pF(28V)	71a(2,7mm)	SOD-123	BB 721
BB 521	Itt	C-Di	=BB 221: verbesserte Linearität/improved charact.	31a	DO-35	=BB 221
BB 523	Itt	C-Di	VHF/UHF Tuning, 32V, 1,9...2.25/20pF(28/1V), <0.8Ω	31a	DO-35	BB 205A,B, BB 405A,B, BB 505B, 1SV148,++
BB 525	Sie	C-Di	SMD, Tuning, 30V, 1,8...2.2/18.5...21.5pF(28/1V)	71a(2,7mm)	SOD-123	-
BB 529	Itt	C-Di	=BB 329: verbesserte Linearität/improved charact.	31a	DO-35	=BB 329
BB 531	Itt	C-Di	VHF Tuning, 32V, 3,15...3.55/50pF(28/1V), <1Ω	31a	DO-35	BB 205G, BB 405G, BB 505G, 1SV124, ++
BB 535	Sie	C-Di	=BB 515:	71a(1,7mm)	SOD-323	1SV214
BB 545	Sie	C-Di	=BB 525:	71a(1,7mm)	SOD-323	-
BB 601	Itt	C-Di	SMD, SATV Tuning, 32V, 0,9...1,2/8...9pF(28/1V)	71a(2,7mm)	SOD-123	1SV186
BB 609 A,B	Aeg,Sie	C-Di	VHF Tuning, OIRT, CATV, 30V, 0,8Ω(100MHz) A=2,6...3/32.5pF(28/1V), B=2,8...3.2/33.5pF(28/1V)	31a	DO-35	BB 106, BB 209, BB 229, BB 409, ++
BB 610	Sie	C-Di	VHF Tuning, 30V, 3,35/69pF(28/1V), 1,3Ω	31a	DO-35	BB 205G, BB 405G, BB 505G, 1SV124, ++
BB 619(A,B)	Phi,Sie	C-Di	SMD, VHF Tuning, Extended Band, 30V, 0,6Ω(100MHz) 2,4...2,9/33.5...41pF(28/1V) A=2,5...3/37.5pF(28/1V), B=2,8...3.2/36pF(28/1V)	71a(2,7mm)	SOD-123	BB 515B,G, BB 723, BB 729...731
BB 620	Phi,Sie	C-Di	SMD, VHF Tuning, Hyperband, 30V, 1,3Ω(100MHz) 2,9...3.4/62...76pF(28/1V)	71a(2,7mm)	SOD-123	-
BB 621	Aeg,Itt	C-Di	=BB 221: SMD	72a(3,4mm)	SOD-80	BB 215, BB 623
BB 622	Aeg,Itt	C-Di	=BB 222: SMD	72a(3,4mm)	SOD-80	BB 215, BB 623
BB 623	Itt	C-Di	SMD, VHF/UHF Tuning, 32V, 2,2/20pF(25/1V), <0,8Ω	72a(3,4mm)	SOD-80	BB 215, BB 621...622
BB 629	Aeg,Itt	C-Di	=BB 329: SMD	72a(3,4mm)	SOD-80	BB 219, BB 631
BB 631	Itt	C-Di	SMD, VHF Tuning, 32V, 3,5/50pF(25/1V), <1Ω(300MHz)	72a(3,4mm)	SOD-80	BB 219, BB 629
BB 639	Sie	C-Di	=BB 619:	71a(1,7mm)	SOD-323	-