

1 SS 25	Unz	Ge-Di	Dem, 40V, 50mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 SS 26	Unz	Ge-Di	Dem, 40V, 50mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 SS 27	Unz	Ge-Di	Dem, 40V, 50mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 SS 28	Unz	Ge-Di	Dem, 30V, 50mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 SS 29	Unz	Ge-Di	Dem, 40V, 50mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 SS 30	Unz	Ge-Di	Dem, 75V, 50mA	31a	DO-7			-
1 SS 31	Unz	Ge-Di	Dem, 50V, 50mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 SS 41	Rhm	Si-Di	SS, 75/100V, 0,13/0,4A, Uf<1V(10mA), <4ns	31a	DO-35			BA 219, 1N4148...49, 1N4446...49, 1SS115,+
1 SS 42	Tos	Si-Di	Schottky-Di, UHF Mx, 5V, 30mA, 900MHz	31a	DO-7			BA 480...481, BAR 19, BAT 29
1 SS 43	Nec	Si-Di	Schottky-Di, Modulator, 5V, 30mA	31a	DO-7			BA 480...481, BAR 19, BAT 29
1 SS 48	Fui	Si-Di	Dual, 70V, 0,1A	5	TO-12			-
1 SS 49	Mat	Si-Di	SS, 35V, 0,1A, <10ns	31a	DO-41			BAY 69, BAY 71, 1N4148...49, 1N4446...49++
1 SS 50	Mat	Si-Di	SS, 50V, 0,1A, <4ns	31a	DO-41			BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 51	Mat	Si-Di	SS, 75V, 0,1A, <10ns	31a	DO-41			BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 52	Nec	Si-Di	SS, 35V, 0,1A, <3ns					BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 53	Nec	Si-Di	S, 35V, 0,1A, <100ns	31a	DO-35			BAX 90, BAX 94, BAY 41...43, 1N4148...49++
1 SS 54	Nec	Si-Di	=1SS53: 75V	31a	DO-35			BAW 49, BAY 43, BAY 72, 1N4148...49, ++
1 SS 55	Nec	Si-Di	=1SS53: 100V	31a	DO-35			BAW 49, BAX 12, BAY 72, 1N4148...49, ++
1 SS 68	Fui	-Di	SS, 40V, 45mA, <6ns	31a	DO-41			-
1 SS 69	Nec	Si-Di	Schottky-Di, UHF Dem, Mx, 4V, 9375MHz	Koax	DO-22			BA 480...481, BAR 19, BAT 29
1 SS 70	Nec	Si-Di	Schottky-Di, UHF Mx, 4V, 30mA, 9375MHz	Koax	DO-22			BA 480...481, BAR 19, BAT 29
1 SS 78	Nec	Si-Di	Schottky-Di, UHF Dem, Mx, 5V, 9375MHz	31a	DO-7			BA 480...481, BAR 19, BAT 29
1 SS 81	Hit	Si-Di	S, 150/200V, 0,2/0,625A, Uf<1V(0,1A), <100ns	31a	DO-35			BA 197...198, BAV 20...21, BAW 50
1 SS 82		Si-Di	=1SS81: 200/250V	31a	DO-35			BA 198, BAV 21
1 SS 83		Si-Di	=1SS81: 250/300V	31a	DO-35			-
1 SS 84	Hit	Si-Di	S, 75V, 0,15A, <50ns	31a	DO-35			BAV 19...21, BAW 49, BAY 43, BAY 72, ++
1 SS 85	Hit	C-Di	VHF Band-S	31a	DO-35			BA 182, BA 243, BA 283, BA 483...484, ++
1 SS 86	Hit	Si-Di	Schottky-Di, TV, UHF Mx, 3V, 30mA	31a	DO-35			-
1 SS 87	Hit	Si-Di	Schottky-Di, TV, UHF Mx, 3V, 15mA	31a	DO-35			-
1 SS 88	Hit	Si-Di	Schottky-Di, UHF Mx, CATV, 10V, 15mA	31a	DO-35			BAT 19, 1SS106
1 SS 90	Hit	Si-Di	Schottky-Di, UHF Mx, 5V, 30mA	31a	DO-7			BA 480...481, BAR 19, BAT 29
1 SS 91(-G,-S)	Njr	C-Di	VHF Band-S	31a	DO-41			BA 182, BA 243, BA 283, BA 483...484, ++
1 SS 92	Rhm	Si-Di	SS, 65/75V, 0,2/0,6A, Uf<1V(0,1A), <2ns	31a	DO-35	1N4148	31a	BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 93	Rhm	Si-Di	=1SS92: 50/55V	31a	DO-35	1N4148	31a	BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 94	Rhm	Si-Di	=1SS92: 35/40V	31a	DO-35	1N4148	31a	BAW 62, BAY 95, 1N4148...49, 1N4446...49++
1 SS 97(1,2)	Nec	Si-Di	Schottky-Di, 10...30V, 35mA	31a	DO-35			HSS 100...102
1 SS 98	Nec	Si-Di	Schottky-Di, 5V, 50mA	31a	DO-35			1S1925
1 SS 99	Nec	Si-Di	Schottky-Di, 5V	31a	DO-35			-
1 SS 101	Nec	Si-Di	Schottky-Di, 70V, 15mA	31a	DO-35			BAR 28, HSS 102, 1N5711
1 SS 102	Nec	Si-Di	SS, 125V, 0,15A, <3ns	31a	DO-41			(BA 203)
1 SS 103	Nec	C-Di	VHF Band-S	71a(4mm)	SOD-23			BA 182, BA 243, BA 283, BA 483...484, ++
1 SS 104	Tos	Si-Di	Uni, 35V, 0,1A	31a	DO-35			BA 127, BA 147/50, BA 187...190, BA 215++
1 SS 106	Hit	Si-Di	Schottky-Di, Dem, SS, 11V, 0,03A	31a	DO-35			BAR 10, BAT 19
1 SS 107	Hit	Si-Di	Schottky-Di, 22V, 15mA	31a	DO-35			BAR 10, 1N5712
1 SS 108	Hit	Si-Di	Schottky-Di, 35V, 15mA	31a	DO-35			HSS 100...102, 1S1992
1 SS 109	Hit	Si-Di	Uni, 90V, 0,15A	31a	DO-41			BA 147/100, BA 189...190, BAY 19...21, ++
1 SS 110	Hit	C-Di	VHF Band-S	31a	DO-34			BA 182, BA 243, BA 283, BA 483...484, ++
1 SS 111	Hit	Si-Di	SS, 20V, 0,15/0,45A, Uf<0,8V(10mA), <2ns	31a	DO-35			BAX 80, BAY 95, 1N4148...49, 1N4446...48++
1 SS 112		Si-Di	=1SS111: 40V	31a	DO-35			BAX 80, BAY 95, 1N4148...49, 1N4446...48++
1 SS 113		Si-Di	=1SS111: 60V	31a	DO-35			BAW 62, BAX 95, 1N4148...49, 1N4446...48++
1 SS 114		Si-Di	=1SS111: 80V	31a	DO-35			BAW 62, BAX 95, 1N4148...49, 1N4446...48++
1 SS 115		Si-Di	=1SS111: 100V	31a	DO-35			BAW 62, BAX 95, 1N4148...49, 1N4446...48++
1 SS 116		Si-Di	=1SS111: 120V	31a	DO-35			-
1 SS 117	Hit	Si-Di	SS, 35V, 0,1A, <3ns	31a	DO-35			BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 118	Hit	Si-Di	SS, 75V, 0,2A, <3ns	31a	DO-35			BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 119	Hit	Si-Di	SS, 35V, 0,15A, <3,5ns	31a	DO-34			BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 120	Hit	Si-Di	=1SS119: 70V	31a	DO-34			BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 121	Hit	Si-Di	S, 75V, 0,2A, <50ns	31a	DO-35			BAV 19...21, BAW 49, BAY 43, BAY 72, ++
1 SS 122(H)	Hit	Si-Di	Uni, S, 400V, 0,15A, <10µs	31a	DO-35			BA 157...159, BA 199/450, BAY 89...91, ++
1 SS 123	Nec	Si-Di	SMD, Dual, SS, 70V, 0,1A, <9ns	35t	SOT-23			-
1 SS 124	Nec	Si-Di	Schottky-Di, UHF Dem, 3V, 30mA, 24GHz	Koax	SOD-50			-
1 SS 125	Nec	Si-Di	Schottky-Di, UHF Dem, 22V, 50mA, 10GHz	Koax	SOD-50			-
1 SS 130	Rhm	Si-Di	SS, 75/100V, 0,13/0,4A, Uf<1V(10mA), <4ns	31a	DO-34			1N4148...49, 1N4446...49, 1SS115...116
1 SS 131	Rhm	Si-Di	SS, 80/90V, 0,13/0,4A, Uf<1,2V(0,1A), <4ns	31a	DO-34			1N4148...49, 1N4446...49, 1SS115...116
1 SS 132	Rhm	Si-Di	SS, 50/55V, 0,12/0,35A, Uf<1,2V(0,1A), <4ns	31a	DO-34			BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 133	Rhm	Si-Di	SS, 35/40V, 0,11/0,3A, Uf<1,2V(0,1A), <4ns	31a	DO-34			BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 134	Rhm	Si-Di	SS, 35/40V, 0,05/0,07A, Uf<0,9V(5mA), <3ns	31a	DO-34			BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 135	Rhm	C-Di	VHF Band-S, 35V, <1,3pF(6V), <0,6Ω(100MHz)	31a	DO-34			BA 182, BA 243, BA 283, BA 483...484, ++
1 SS 136	Rhm	Si-Di	SS, 65/75V, 0,2/0,6A, Uf<1V(0,1A), <2ns	31a	DO-34			BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 137	Rhm	Si-Di	=1SS136: 50/55V	31a	DO-34			BAW 62, BAX 95, 1N4148...49, 1N4446...49++
1 SS 138	Rhm	Si-Di	=1SS136: 35/40V	31a	DO-34			BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 139	Rhm	Si-Di	S, 80/90V, 0,13/0,4A, Uf<1,2V(0,1A), <50ns	31a	DO-35			BAV 19...21, BAW 49, BAY 43, BAY 72, ++
1 SS 140	Rhm	Si-Di	S, 50/55V, 0,12/0,35A, Uf<1,2V(0,1A), <50ns	31a	DO-35			BAY 18...21, BAW 49, BAY 42, BAY 72, ++
1 SS 141	Rhm	Si-Di	S, 35/40V, 0,11/0,3A, Uf<1,2V(0,1A), <50ns	31a	DO-35			BAV 18...21, BAW 49, BAY 41, BAY 72, ++
1 SS 142	Rhm	Si-Di	S, Uni, 250/300V, 0,2/0,625A, Uf<1V(0,1A), <400ns	31a	DO-35			BA 157...159, BY 204/4, BY 206...207, ++
1 SS 143	Rhm	Si-Di	=1SS142: 200/250V	31a	DO-35			BA 157...159, BY 204/4, BY 206...207, ++
1 SS 144	Rhm	Si-Di	=1SS142: 150/200V	31a	DO-35			BA 157...159, BY 204/4, BY 206...207, ++
1 SS 145	Rhm	Si-Di	=1SS142:	31a	DO-34			-1SS142
1 SS 146	Rhm	Si-Di	=1SS143:	31a	DO-34			-1SS143
1 SS 147	Rhm	Si-Di	=1SS144:	31a	DO-34			-1SS144
1 SS 148	Tos	Si-Di	SS, 35V, 0,1A, <4ns	31a	DO-34			BA 318, BAY 38, 1N4148...49, 1N4446...49++
1 SS 149	Hit	Si-Di	Uni, 250V, 0,15A, <5µs	31a	DO-35			BA 157...159, BY 204/4, BY 206...207, ++
1 SS 150	Hit	C-Di	VHF Band-S	31a	DO-35			BA 182, BA 243, BS 283, BA 483...484, ++
1 SS 151	Hit	Si-Di	Schottky-Di, Dem, S, 4V, 30mA	31a	DO-35			BA 480...481, BAR 19, BAT 29
1 SS 152	Hit	C-Di	VHF Band-S	31a	SOD-17			BA 182, BA 243, BS 283, BA 483...484, ++
1 SS 153	Nec	C-Di	SMD, VHF Band-S	35p	SOT-23			-
1 SS 154	Tos	Si-Di	SMD, UHF, S, 6V, 0,03A, 0,8pF	35c	SOT-23			-
1 SS 155	Tos	C-Di	(Band-S)	31a	DO-34			-
1 SS 157	Say	Ge-Di	Dem, 40V, 50mA	31a	DO-35			AA 113, AA 119, 1N34, 1N54, 1N60
1 SS 158	Say	Ge-Di	Dem, 50V, 50mA	31a	DO-35			AA 113, 1N34, 1N54, 1N60
1 SS 161	Njr	C-Di	VHF Band-S	31a	DO-34			BA 182, BA 243, BA 283, BA 483...483, ++
1 SS 162	Njr	C-Di	UHF Band-S	31a	DO-34			BA 244, BA 282, BA 282, BA 482
1 SS 163	Hit	Si-Di	SS, 35V, 0,15A, <4ns	31a	DO-34			BA 318, BAY 38, 1N4148...49, 1N4446...49++